


10/ 691 313

cgc



IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Patent: No. 7,107,029

Issue Date: Sept. 12, 2006

Application No.: 10/691,313

Confirmation No.: 6401

Applicant(s): Mason

Filed: October 22, 2003

Title: Reduced Power Consumption

Attorney Docket No.: 894A.0001.U1 (US)

Customer No.: 29,683

ATTN: Certificate of Correction Branch

Commissioner For Patents

P.O. Box 1450

Alexandria, VA 22313-1450

Certificate
MAY 23 2007
of Correction

Request For Certificate Of Correction

Sir:

The Notice of Allowability mailed 03/26/2006 incorrectly stated that the certified copy of the priority document had been received by the USPTO. Upon further review of applicant's attorney's file, this appears to have been incorrect. Therefore, enclosed is a certified copy of the priority document. MPEP 201.14(a) states that a certificate of correction can be filed to have the certified copy considered after publication of the patent. Thus, the USPTO is requested to consider the enclosed certified copy of the priority document to perfect the claim of priority under 35 U.S.C. 119.

Although it is believed that no fee is due with this request, the USPTO is authorized to charge deposit account 50-1924 if it believes a fee is due.

MAY 23 2007

Respectfully submitted,

Mark F. Harrington

Mark F. Harrington (Reg. No. 31,686)

5/15/07

Date

Customer No.: 29683

Harrington & Smith, PC

4 Research Drive

Shelton, CT 06484-6212

203-925-9400

CERTIFICATE OF MAILING

I hereby certify that this correspondence is being deposited with the United States Postal Service as first class mail on the date shown below in an envelope addressed to: Commissioner For Patents, P.O. Box 1450, Alexandria, VA 22313-1450.

May 15, 2007
Date

Debra Pergeth
Name of Person Making Deposit

MAY 23 2007

**UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION**Page 1 of 1

PATENT NO. : 7,107,029

APPLICATION NO.: 10/691,313

ISSUE DATE : Sep. 12, 2006

INVENTOR(S) : Mason

It is certified that an error appears or errors appear in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

The certified copy of the priority document has been received.

MAILING ADDRESS OF SENDER (Please do not use customer number below):

Harrington & Smith, PC
4 Research Drive, Shelton, CT 06484

MAY 23 2007

This collection of information is required by 37 CFR 1.322, 1.323, and 1.324. The information is required to obtain or retain a benefit by the public which is to file (and by the USPTO to process) an application. Confidentiality is governed by 35 U.S.C. 122 and 37 CFR 1.14. This collection is estimated to take 1.0 hour to complete, including gathering, preparing, and submitting the completed application form to the USPTO. Time will vary depending upon the individual case. Any comments on the amount of time you require to complete this form and/or suggestions for reducing this burden, should be sent to the Chief Information Officer, U.S. Patent and Trademark Office, U.S. Department of Commerce, P.O. Box 1450, Alexandria, VA 22313-1450. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: **Attention Certificate of Corrections Branch, Commissioner for Patents, P.O. Box 1450, Alexandria, VA 22313-1450.**

If you need assistance in completing the form, call 1-800-PTO-9199 and select option 2.

Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

The undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents originally filed in connection with patent application GB0324266.6 filed on 16 October 2003.

I do hereby certify that the attached copy of the request for grant of a Patent (Form 1/77) bears an amendment, effected by this office, following a request by the applicant and agreed to by the Comptroller-General.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1985 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.


Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed *Hebehan*
Dated 18 April 2007

23 2007

The
Patent
Office

Request for grant of a patent



1/77

The Patent Office
Cardiff Road
Newport
Gwent NP10 8QQ

1. Your reference

NOKO/P31634 GB
PAT 03008 GB

2. Patent application number

0324266.6

16 OCT 2003

3. Full name, address and post code of the or
of each applicant

Nokia Corporation
Keilalahdentie 4
02150 Espoo
Finland

Patents ADP Number

7652217005

If the applicant is a corporate body, give the
country/state of its incorporation

Finland

4. Title of the invention

Reduced Power Consumption

5. Name of your agent
"Address for service" in the United Kingdom
to which all correspondence should be sent

Saiful Khan
Nokia IPR Department
Nokia House, Summit Avenue
Farnborough, Hants
GU14 0NG

Eric Porter Clarkson
Park View House
55 The Rope Walk
Nottingham
NG1 5DN
UK. (See f5177)
25-10-04

Patents ADP number

7577638001
1305010

6. If you are declaring priority from one or more
earlier patent applications, give the country and
the date of filing of the or of each of these earlier
applications and the or each application number

Country Priority Application Number Date of Filing

Kf 27/01

7. If this application is divided or otherwise
derived from an earlier UK application,
give the number and the filing date of the
earlier application

Number of earlier application

Date of Filing

8. Is a statement of inventorship and of right
to grant of a patent required in support of
this request? (Answer 'Yes' if:

Yes

- a) any applicant named in part 3 is not an inventor, or
- b) there is an inventor who is not named as an applicant, or
- c) any named applicant is a corporate body.

1 2 3 2007/1

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form.
Do not count copies of the same document

Continuation sheets of this form

Description	15
Claims(s)	5
Abstract	1
Drawing(s)	7

10. If you are also filing any of the following state how many against each item.

Priority documents

Translation of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77)	2
------------------------------------------------------------------------------	---

Request for preliminary examination and search (Patents Form 9/77)	1
--------------------------------------------------------------------	---

Request for substantive examination
(Patents Form 10/77)

Any other documents
(please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

Saiful Khan

15/10/03

12. Name and daytime telephone number of person to contact in the United Kingdom

Saiful Khan - 01252 867597


**The
Patent
Office**




**Statement of inventorship and of
right to grant of a patent**

7/77

The Patent Office
Cardiff Road
Newport
Gwent NP10 8QQ



1.	Your reference	PAT 03008 GB
2.	Patent application number	0324266.6
3.	Full name of the or of each applicant	Nokia Corporation
4.	Title of the invention	Reduced Power Consumption
5.	State how the applicant(s) derived the right from the inventor(s) to be granted a patent	By virtue of Section 7(2)(c)
6.	How many, if any, additional Patents Forms 7/77 are attached to this form?	One
7.	I/We believe that the person(s) named over the page (and on any extra copies of this form) is/are the inventor(s) of the invention which the above patent application relates to. Signature  Date 0/16/03 Saiful Khan	
8.	Name and daytime telephone number of person to contact in the United Kingdom	Saiful Khan - 01252 867597

MAY 23 2007

Patents Form 7/77

Enter the full names, addresses and postcodes of the inventors in the boxes and underline the surnames

KEN MASON
2 Ayrshire Gardens
Ansells Farm
Fleet
Hampshire
GU13 8TS

7129059

Reminder
Have you signed the form?

Patents Form 7/77

REDUCED POWER CONSUMPTION

5 Field of the Invention

The present invention relates to the field of frequency modulated radio receivers (FM radios), and particularly the incorporation of an FM radio into a multimedia device.

10

Background to the Invention

A multimedia device may be a piece of mobile communication equipment such as a mobile telephone, PDA, or the like having functionality over and
15 above a basic FM radio receiver. The multimedia device may however have no electronic functions other than those of a radio receiving apparatus.

The radio data system (RDS) is intended for application to VHF/FM sound broadcasts in the range 87.5 MHz to 108 MHz; these may carry either
20 stereophonic or monophonic programs. The main objectives of RDS are to enable improved functionality of FM receivers and to make them more user-friendly by using features such as program identification, program service menu display and where applicable, automatic tuning for radios incorporated into mobile devices. This is done by providing (and using) information to
25 supplement the audio radio transmission.

MAY 23 2007

RDS is defined by the European Broadcasting Union (EBU)/Cenelec Standard EN50067: 1998, "Specification of the Radio Data System". This standard is compatible with the United States radio broadcast data system (RBDS)
30 defined by the US National Radio Systems Committee in the specification of the radio broadcast data system, dated 9 April 1998. In the following, it should be understood that the term RDS refers to both the Radio Data

MAY 23 2007

the Radio Broadcast Data System, unless otherwise specified by the person skilled in the art.

Figure 1 shows the structure of the baseband coding of the RDS. For example see Figure 8 of EN50067: 1998. The largest element of the structure is called a group, consisting of 104 bits. Each group contains four blocks of 26 bits each. Each block contains an information word and a check word. Each information word comprises 16 bits, and each check word comprises 10 bits. The format and addressing structure of the information word of Blocks 1 and 2 are illustrated in Figure 2A (see Figure 9 of EN50067: 1998), and of the information words of Blocks 1, 2, 3 and 4 according to group type (see Block 2, Figure 3 and explanation below) in Figure 2B (i and ii).

As can be seen from Figure 2, the first block (Block 1) in every group always contains a program identification (PI) code. Furthermore, the first four bits of the second block (Block 2) of every group are allocated to a 4-bit code that specifies how the information within the group is to be applied. According to the Standard, groups are referred to as type 0 to 15 according to binary weighting $A_3=8$, $A_2=4$, $A_1=2$, $A_0=1$. For each type (0 to 15) two versions can be defined, versions A and B (Figure 3). The version is specified by a fifth bit (B_0) of block 2, and a mixture of version A and version B groups may be transmitted on one particular FM radio station. The Standard defines that if $B_0=0$, the PI code is inserted in block 1 only (version A) and if $B_0=1$, the PI code is inserted in block 1 and block 3 of all group types (version B).

25

The Standard defines that each block 2 contains a Group Type Code (GTC) defining the nature of the information word of the block (see Figure 3, which provides a table of the group type codes for both versions A and B of the RDS encoding system and a brief description of the data content of each group). Furthermore, six locations in block 2 of every group are occupied by a program type code (PTY) and the traffic program identification (TP) code (Figure 2 and Figure 3).

30

The PI, PTY and TP codes can be decoded without reference to any block outside the ones that contain information relating to one of these codes. This is important to minimise acquisition time for these kinds of message and to retain the advantages of the short (26-bit) block length. To permit this to be done for the PI codes in block 3 of version B groups, a special offset word (commonly defined as C') is used in block 3 of version B groups. The occurrence of offset C' in block 3 of any group can then be used to indicate directly that block 3 is a PI code, without any reference to the value of B₀ in block 2.

10

Figure 4 shows a circuit 1 suitable for receiving FM radio including an RDS demodulator 5 and an RDS decoder 6. The output of the RDS decoder 6 is an RDS data signal which is input to a host processor 7 of a device. The circuit 1 is arranged such that an FM signal is received at the antenna 2 and demodulated by the very high frequency (VHF)/FM demodulator 3, which outputs a multiplexed signal to an audio decoder 4 and an RDS signal demodulator 5. The audio decoder 4 outputs a program audio signal which may consist of either a single sound channel (monophonic) or two sound channels (stereophonic). The program audio signal output by audio decoder 4 may then be amplified and used by the multimedia device. The RDS signal demodulator 5 demodulates the RDS signal from the multiplexed signal and outputs this to an RDS decoder 6. The RDS decoder 6 outputs an RDS data signal corresponding to the information word of a block. The RDS decoder 6 signals an interrupt to the host processor 7 when a new data block has been decoded. This can be after every block, which corresponds to one interrupt every 22ms.

It is common for multimedia devices to incorporate an idle mode in order to reduce current consumption and increase battery life. In such an idle mode, the host processor of such a multimedia device may be substantially deactivated, such that a core of the processor is only activated in response to a particular flag being set in an on-chip register. This may occur, for example, upon the depression of a key of the multimedia device. Typically an FM radio

application incorporated into a multimedia device operating in such an idle mode allowing for low current consumption by the radio. However, with the addition of a circuit for decoding RDS as shown in figure 4, the processor of the multimedia device must wake up every 22 or 44ms to service the interrupt. This activity of the host processor results in an increase in current consumption. In the case of the multimedia device being battery operated, the inclusion of a circuit capable of decoding RDS to an FM radio application may lead to a reduced radio listening time and further a reduced multimedia device operation time.

10

One option for mitigating this problem is to incorporate buffering in the circuit so that the host processor may receive an interrupt once every two blocks have been decoded, corresponding to an interrupt interval of 44ms. However, this still requires the processor to be activated frequently and to be activated even if non-required data is being received.

15

It is an aim of embodiments of the present invention to solve at least one of the problems as described above.

20 Summary of the Invention

According to a first aspect of the invention there is provided a radio frequency receiver for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields containing supplementary data transmitted with the radio station signal, said receiver comprising:

25

- a host processor for processing said supplementary data;

- a supplementary data demodulator and decoder for demodulating and decoding a received radio signal to generate a stream of bits representing one or more information word fields;

30

- a information word type memory for storing one or more information word type fields;

detection circuitry arranged to receive and compare the information word type field decoded by the supplementary data decoder with one or more information word type fields stored in the information word type memory, and to provide a matched condition signal in response to a match between one or more decoded information word type fields and one or more of said corresponding stored information word types fields, and wherein the receiver is arranged to, in response to the matched condition signal, cause the corresponding supplementary data to be processed by means of the host processor.

10

The receiver and the supplementary data may conform to RDS/RBDS standard. In such cases, the receiver may be arranged to store one or more Block 2 codes and the detection circuitry may be arranged to provide the matched condition signal in response to a match between the one or more received decoded Block 2 information word type fields and one or more of said corresponding stored Block 2 information word types fields.

15

The information word type memory may be arranged to store one or more GTC(s), one or more TP code(s), one or more PTY code(s) or one or more TA code(s).

20

The information word type memory may be programmable. Specifically, information word type memory may be user-programmable.

The receiver may be arranged to process the supplementary data using the host processor during an already non-idle period of the host processor. This non-idle period may be a period when the host processor is processing GSM/TDMA/WCDMA data.

25

The receiver may further comprise a buffer memory for storing the decoded supplementary data prior to the decoded supplementary being processed by the host processor. The buffer memory may be a FIFO (first in, first out) memory. The receiver may further comprise a latch responsive to the

30

detection circuitry for controlling the flow of supplementary memory. The latch may be arranged to receive at a data input supplementary data, and at a clock input a match condition signal by the detection circuitry responsive to a match. The receiver is arranged such that the host processor reads the contents of the buffer memory upon receipt of an interrupt. The interrupt may be generated by circuitry external to the receiver, may be initiated by the user, or generated in response to the buffer memory reaching its capacity, or generated in response to an instruction to process GSM burst data.

10

In the embodiment that comprises a buffer memory, the receiver may be arranged such that the host processor reads the contents of the buffer memory during GSM burst activity. The receiver may be incorporated into a device for communicating over a GSM network, and said device may be a mobile phone.

15

The receiver may be arranged to be capable of receiving and decoding the radio station signal.

20 The radio station signal may be an audio signal and the receiver may be arranged to be capable of presenting the audio signal to a user, for example by means of a loudspeaker or other audio reproduction means.

The radio station signal may be a frequency modulated signal or an amplitude modulated signal.

25

In a second aspect, the present invention provides a mobile terminal comprising a radio frequency receiver for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields containing supplementary data transmitted with the radio station signal, said receiver comprising:

30

a host processor for processing said supplementary data;

a supplementary data demodulator and decoder for demodulating and decoding a received radio signal to generate a stream of bits representing one or more information word fields;

5 a information word type memory for storing one or more information word type fields;

detection circuitry arranged to receive and compare the information word type field decoded by the supplementary data decoder with one or more information word type fields stored in the information word type memory, and
10 to provide a matched condition signal in response to a match between one or more decoded information word type fields and one or more of said corresponding stored information word types fields, and wherein the receiver is arranged to, in response to the matched condition signal, cause the corresponding supplementary data to be processed by means of the host
15 processor.

In a third aspect, the present invention provides a method for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields
20 containing supplementary data transmitted with the radio station signal, said method comprising:

processing said supplementary data by a processing means;

demodulating and decoding a received radio signal to generate a stream of bits representing the one or more information word fields;

25 storing one or more information word type fields in an information word field store;

receiveing and comparing the information word type field decoded by the decoder with one or more of the stored information word type fields, and in response to a match therebetween, causing the corresponding
30 supplementary data to be processed by group to be processed.

MAY 23 2007

Description of the Drawings

The present invention will now be described by way of reference to the accompanying drawings.

5

Figure 1 shows a structure of RDS/RBDS baseband coding as is known in the art and as shown in Section 2.1 of EN50067: 1998.

10

Figure 2 A shows a information word format and addressing structure of an RDS signal, as is known in the art and as shown in Section 2.2 of EN50067: 1998.

15

Figure 2B (i and ii) shows the information word format and addressing structure of Blocks 1, 2, 3 and 4 according to group type.

Figure 3 shows a table of group type codes used in the RDS messages, as are known in the art and as shown in Section 3.1.3 of EN50067: 1998.

20

Figure 4 shows a prior art apparatus suitable for receiving an FM audio signal and a corresponding RDS data signal.

25

Figure 5 shows an apparatus suitable for receiving an FM audio signal and a corresponding RDS data signal in accordance with an embodiment of the present invention.

30

Description of Preferred Embodiments of the Present Invention

Figure 5 shows a preferred embodiment of the present invention, featuring a circuit 10 sharing some features with that shown in Figure 4. Features of

Figure 5 having similar functions to features of Figure 4 have been given like reference numerals. Only the differences are described herein.

The circuit 10 includes a detection circuitry 11 and an information word type (IWT) memory 12. The host processor 7 contains a register 13 and a processor core 14. The IWT memory 12 contains at least one group type code (GTC). The one or more group type codes may be written to the memory by the host processor 7, or another piece of circuitry (not shown). Alternatively, the IWT memory 12 may be a read only memory (ROM) containing one or more predetermined GTCs.

The detection circuitry 11 receives the RDS data group signal output by the RDS decoder 6. The RDS data group signal includes the GTC in the information word of Block 2. The detection circuitry 11 identifies the received GTC from the RDS data group signal and searches for a match between the received GTC, and the one or more GTCs stored in the GT memory 12.

If a positive match is found by the detection circuitry 11, then the detection circuitry 11 outputs a match signal to the host processor 7, which causes the host processor to set a flag in a register 13. The setting of this flag causes the processor core 14 to be activated and process the corresponding RDS data block received from the RDS decoder 6. Alternatively, if no match is found between the received GTC and the one or more GTCs stored in the IWT memory 12, then no flag is set and the received GTC is discarded and the RDS data group signal is not processed by the processor core 14.

In another embodiment, the IWT memory 12 stores program type (PTY) codes and/or traffic programme identification (TP) codes. In these embodiments, the detection circuitry 11 outputs a flag in response to the detection of a match between a PTY code and/or a TP code identified in the received signal and a respective PTY code and/or TP code in the IWT memory 12.

In a preferred embodiment, the IWT memory 12 contains one or more word codes and the detection circuitry 11 is arranged to output a flag in response to the detection of a corresponding match. In a specific embodiment, the IWT memory 12 stores one or more PTY, TP, TA and GTC codes. The detection circuitry 11 is arranged to output a flag in response to the detection of one or more corresponding matches. A PTY code match is possible irrespective of the other bits in Block 2.

The IWT memory 12 may contain one or more Block 1, Block 2, Block 3 and/or Block 4 information word codes and the detection circuitry 11 is arranged to output a flag upon the detection of a corresponding match.

The IWT memory codes for storing in the memory 12 are preferably chosen to assist in the enhancement of the user experience whilst at the same time reducing power consumption of processor 7.

The configuration of the data connections between the units shown in the figures is not limited to those examples that are shown. For example, the RDS decoder need not be connected directly to the host processor. In an alternative example, some or all of the units that exchange data could be interconnected by a common data bus. The audio decoder 4 may be powered down while the receiver is looking for a match. Upon detection of a match by the detection circuitry 11, the audio decoder 4 may be powered up in order to output the audio channel or channels of the received signal. Thus, the audio output of the receiver is only activated for a predetermined program type.

Figure 6 shows an alternative apparatus, featuring a circuit 20 sharing some features shown in Figure 5. Features of Figure 6 having similar functions to features of Figure 5 have been given like reference numerals. Only the differences are described herein.

The circuit 20 includes an RDS decoder 6, a detection circuit 11, and a host processor 7 as shown in figure 5. Circuit 20 further comprises a latch 21 and

an RDS memory 22 connected in series between the RDS decoder 6 and the host processor 7. The latch 21 may be a D-type latch. The latch 21 receives as a data input the output of RDS decoder 6, and as a clock input the output of detection circuitry 11. The RDS memory 22 receives as an input the output of the latch 21. The RDS memory 22 may be accessed by the host processor 7.

The RDS decoder 6 and detection circuitry 11 generate the same outputs as described above. The latch 21 acts so as to pass only data received from the RDS decoder when the match signal output by the detection circuitry 11 is set. This data is then stored in RDS memory 22, ready for access by the host processor 7. Hence, the circuit 20 acts so as to only buffer, using RDS memory 22, received blocks of the RDS data signal that are determined as being relevant to the host processor 7 by the IWT memory 12.

In an alternative apparatus the RDS memory 22 is configured to store the contents of blocks 2, 3 (or 3') and 4 in response to a GTC match in block 2. This may be carried out by implementing a timer on the clock input of latch 21. The timer is arranged to output a pulse upon detection of a match by the detection circuitry 11. The length of this pulse corresponds to the length of time required for blocks 2, 3 (or 3') and 4 to pass through the latch and into the RDS memory 22. In the preferred embodiment, the pulse length is 66ms.

The RDS memory 22 may be a FIFO memory. Alternatively, the RDS memory 22 may be any other suitable type of memory.

The host processor 7 is configured to read from the RDS memory 22 upon receipt of an interrupt. This interrupt may be generated by the other circuitry of the multimedia device, and may or may not be connected to the FM radio of the multimedia device. The interrupt may for example be generated by a user performing a task with the multimedia device that requires the use of the host processor 7 that is not related to the radio of the multimedia device. Alternatively, the interrupt may be triggered by the user. For example, the user

may select a refresh station list option incorporated into the device. In another alternative apparatus, the interrupt may be a response to the RDS Memory 22 reaching its capacity.

- 5 In an embodiment of the present invention, the multimedia device is a communications device capable of operating in a telecommunication system such as GSM, UMTS, or the like. For example, in the case of a multimedia device having GSM functionality the host processor 7 would normally be in idle mode in a time interval between transmitting data bursts to a network, which is called GSM idle mode. The host processor 7 of such a multimedia device receives interrupts intermittently in order to process GSM burst data. In such a device, it would be possible for the host processor to access and process the data stored in the RDS memory 22, upon the receipt of an interrupt to process GSM burst data. The invention is correspondingly applicable to TDMA and
- 10 WCDMA (TDD/FDD) and more generally 2G, 2.5G, 3G, 4G and variations thereof.

Accordingly, in embodiments of the present invention the host processor can be required to process RDS data relatively infrequently receiving fewer

20 interrupts than would be experienced using a conventional RDS decoding circuit. Embodiments of the present invention can thus advantageously allow reduced power consumption in a multimedia device incorporating a radio receiver incorporating RDS.

- 25 As described above, the IWT memory may store information word type codes which are compared with the information word type codes of received groups to determine whether they should be processed by the host processor. In the specific example of an RDS system, the IWT memory may store 4-bit group type GTCs (including the 4 bits A_3 , A_2 , A_1 , and A_0) or 5-bit group types
- 30 including GTCs and version numbers (including the 5 bits A_3 , A_2 , A_1 , and A_0 and B_0). In each case, a match between a stored IWT and a received IWT may be determined when each of the bits of the stored IWT equal each corresponding bit of the received IWT. In another embodiment a match may

be declared when a predetermined sub-set of the bits match: for instance the 4 bits A_3 , A_2 , A_1 , and A_0 in the case of a 5-bit stored group type.

5 In an alternative embodiment of the present invention, the radio receiver is powered down when receiving blocks 3 (or 3'), 4 and 1 and is only powered up for receiving block 2. The receiver does this by counting a specific number of RDS clock cycles after receiving a block 2 such that the receiver powers up to receive the next block 2. This is advantageous when the receiver is used in a background mode to either wake up when a specific group, program type
10 code (PTY) or any other group type code specified is received. In this embodiment, the receiver may be programmed so as to only wake up in order to receive the block 2, and then to only send an interrupt to the processor upon receipt of a block containing an alternate frequency code. This advantageously allows the receiver to maintain an alternate frequency list
15 while the user is not listening to the radio channel, or alternatively allows the radio receiver to be powered up when a certain program type is detected.

Embodiments may be implemented using a power management integrated circuit incorporated into the multimedia device. The power management
20 integrated circuit is adapted to allow individual circuitry or areas of circuitry within the multimedia device to be switched off or on independently. Such a power management integrated circuit advantageously allows the multimedia device to reduce current consumption during the performance of different functions. The radio receiver may be powered by a power management
25 integrated circuit. A switch incorporated into the power management integrated circuit provides power to the radio receiver, said switch being responsive to an output of the RDS decoder 6. The RDS decoder 6 may also be powered by the power management integrated circuit.

30 The above embodiment advantageously allows the receiver to enter a substantially powered down state wherein far less current is drawn for three quarters of the time, when blocks containing group type codes that are not stored in the memory are received. The receiving circuitry is only fully

powered up for a quarter of the time, when a block 2 is received for a short period of time after a block 2 having a GTC that is stored in memory is received.

- 5 An advantage of embodiments of the present invention as described is that the RDS data is only output in response to a match, which can only occur when the decoder is synchronized with the RDS data signal of an appropriate radio channel. In such embodiments the previously discussed problem of incorrect RDS data being output when the receiver is not synchronised may be addressed.
- 10

Embodiments of the present invention have been described in the context of FM radio and the RDS and RBDS standards. However, it should be appreciated that embodiments of the present invention can be used with any other type of information system featuring the broadcast of supplementary data with a radio station. This may, for example, be the SWIFT system defined in standard ETS-300751 issued by the European Telecommunications Standards Institute. Alternatively, this may take the form of the inclusion of supplementary data applied to amplitude modulation broadcast stations. The radio signals are preferably non-televisual signals. The information word of the supplementary data may contain error detection and/or error correction capability.

15

20

The applicant hereby discloses in isolation each individual feature described herein and any combination of two or more such features, to the extent that such features or combinations are capable of being carried out based on the present specification as a whole in the light of the common general knowledge of a person skilled in the art, irrespective of whether such features or combinations of features solve any problems disclosed herein, and without limitation to the scope of the claims. The applicant indicates that aspects of the present invention may consist of any such individual feature or combination of features. In view of the foregoing description it will be evident

25

30

to a person skilled in the art that various modifications may be made within the scope of the invention.

CLAIMS

1. A radio frequency receiver for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields and supplementary data transmitted with the radio station signal, the receiver comprising:
- a host processor for processing said supplementary data;
 - a supplementary data demodulator and decoder for demodulating and decoding a received radio signal to generate a stream of bits representing one or more information word fields;
 - a information word type memory for storing one or more information word type fields;
- detection circuitry arranged to receive and compare the information word type field decoded by the supplementary data decoder with one or more information word type fields stored in the information word type memory, and to provide a matched condition signal in response to a match between one or more decoded information word type fields and one or more of said corresponding stored information word types fields, and wherein the receiver is arranged to, in response to the matched condition signal, cause the corresponding supplementary data to be processed by means of the host processor.
2. A receiver as claimed in claim 1, wherein the receiver and the supplementary data conform to RDS standard.
3. A receiver as claimed in claim 1, wherein the receiver and the supplementary data conform to RBDS standard.
4. A receiver as claimed in claim 1, wherein the receiver and the supplementary data conform to RDS standard information word type memory and wherein the receiver is arranged to store one or more

Block 2 codes and the detection circuitry is arranged to provide the matched condition signal in response to a match between the one or more received decoded Block 2 information word type fields and one or more of said corresponding stored Block 2 information word types fields.

5

5. A receiver as claimed in claim 1, wherein the receiver and the supplementary data conform to RBDS standard information word type memory and wherein the receiver is arranged to store one or more Block 2 codes and the detection circuitry is arranged to provide the matched condition signal in response to a match between the one or more received decoded Block 2 information word type fields and one or more of said corresponding stored Block 2 information word types fields.

10

15

6. A receiver as claimed in claim 1, wherein the information word type memory is arranged to store one or more GTC(s).

7. A receiver as claimed in claim 1, wherein the information word type memory is arranged to store one or more TP code(s).

20

8. A receiver as claimed in claim 1, wherein the information word type memory is arranged to store one or more PTY code(s).

9. A receiver as claimed in claim 1, wherein the information word type memory is arranged to store one or more TA code(s).

25

10. A receiver as claimed in claim 1, wherein the information word type memory is programmable.

30

11. A receiver as claimed in claim 1, wherein the information word type memory is user-programmable.

12. A receiver as claimed in claim 1, wherein the receiver is arranged to process the supplementary data using the host processor during an already non-idle period of the host processor.
- 5 13. A receiver as claimed in claim 1, wherein the receiver is arranged to process the supplementary data using the host processor during an already non-idle period of the host processor, and wherein the non-idle period is a period when the host processor is processing GSM data.
- 10 14. A receiver as claimed in claim 1, wherein the receiver is arranged to process the supplementary data using the host processor during an already non-idle period of the host processor, and wherein the non-idle period is a period when the host processor is processing TDMA data.
- 15 15. A receiver as claimed in claim 1, wherein the receiver is arranged to process the supplementary data using the host processor during an already non-idle period of the host processor, and wherein the non-idle period is a period when the host processor is processing WCDMA data.
- 20 16. A receiver as claimed in claim 1, further comprising:
a buffer memory for storing the decoded supplementary data prior to the decoded supplementary being processed by the host processor.
- 25 17. A receiver as claimed in claim 16, wherein said buffer memory is a FIFO memory.
- 30 18. A receiver as claimed in claim 16 or 17, further comprising a latch responsive to the detection circuitry for controlling the flow of supplementary data to the buffer memory.

19. A receiver as claimed in claim 18, wherein said latch is arranged to receive at a data input the decoded supplementary data, and at a clock input a match condition signal generated by the detection circuitry responsive to a match.
- 5
20. A receiver as claimed claim 16, wherein the receiver is arranged such that the host processor reads the contents of the buffer memory upon receipt of an interrupt.
- 10
21. A receiver as claimed in claim 20, wherein the interrupt is generated by circuitry external to the receiver.
22. A receiver as claimed in claim 20, wherein the interrupt is initiated by the user.
- 15
23. A receiver as claimed in claim 20, wherein the interrupt is generated in response to the buffer memory reaching its capacity.
24. A receiver as claimed in claim 20, wherein the interrupt is generated in response to an instruction to process GSM burst data.
- 20
25. A receiver as claimed in any one of claims 16, wherein the receiver is arranged such that the host processor reads the contents of the buffer memory during GSM burst activity.
- 25
26. A receiver as claimed in claim 25, wherein said receiver is incorporated into a device for communicating over a GSM network.
27. A receiver as claimed in claim 26, wherein said device for communicating over a GSM network is a mobile phone.
- 30
28. A receiver as claimed in claim 1, wherein the receiver is arranged to be capable of receiving and decoding the radio station signal.

29. A receiver as claimed in claim 1, wherein the radio station transmits an audio signal and the receiver is arranged to be capable of receiving and outputting the audio signal to a user.
- 5 30. A receiver as claimed in claim 1, wherein the radio station signal is a frequency modulated signal.
- 10 31. A receiver as claimed in claim 1, wherein the radio station signal is an amplitude modulated signal.
32. A mobile terminal comprising a receiver as claimed in claim 1.
- 15 33. A method for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields containing supplementary data transmitted with the radio station signal, said method comprising:
- 20 processing said supplementary data by a processing means;
 demodulating and decoding a received radio signal to generate a stream of bits representing the one or more information word fields;
 storing one or more information word type fields in an information word field store;
- 25 receiving and comparing the information word type field decoded by the decoder with one or more of the stored information word type fields, and in response to a match therebetween, causing the corresponding supplementary data to be processed by group to be processed.
- 30 34. A receiver as hereinbefore described with reference to Figures 5 and 6.
35. A method of processing supplementary data as hereinbefore described with reference to Figures 5 and 6.

ABSTRACT

REDUCED POWER CONSUMPTION

- 5 A radio frequency receiver for receiving supplementary data transmitted with a radio station signal, said supplementary data comprising one or more information word fields containing supplementary data transmitted with the radio station signal, said receiver comprising:
- 10 a host processor for processing said supplementary data;
- a supplementary data demodulator and decoder for demodulating and decoding a received radio signal to generate a stream of bits representing one or more information word fields;
- a information word type memory for storing one or more information word type fields;
- 15 detection circuitry arranged to receive and compare the information word type field decoded by the supplementary data decoder with one or more information word type fields stored in the information word type memory, and to provide a matched condition signal in response to a match between one or more decoded information word type fields and one or more of said
- 20 corresponding stored information word types fields, and wherein the receiver is arranged to, in response to the matched condition signal, cause the corresponding supplementary data to be processed by means of the host processor.

25

Figure 5

30

1/7

FIGURE 1





FIGURE 2



MAY 23 2007

2/7

FIGURE 2 B (ii)

Group Type Code	BLOCK 1										BLOCK 2										BLOCK 3 (or 3)										BLOCK 4																																														
	2	4	8	12	16	20	24	28	30	31	32	34	36	37	38	39	40	41	42	44	46	48	50	52	53	56	60	64	68	70	72	74	76	78	82	86	90	94	96	98	100	102	104																																		
0 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	TA	MS	DI	C ₁	C ₂	Checkword + Offset B										A F	A F	Checkword + Offset C										PS name seg.										Checkword + Offset D																							
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	TA	MS	DI	C ₁	C ₂	Checkword + Offset B										PI Code										Checkword + Offset C										PS name seg.										Checkword + Offset D															
1 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	Radio Paging										Checkword + Offset B										LA	Slow labelling codes										PI Number Code										Checkword + Offset D																			
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	Spare Bits										Checkword + Offset B										PI Code										Checkword + Offset C										PI Number Code										Checkword + Offset D										
2 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	AB	Text Address segment										Checkword + Offset B										Radioext Segment										Checkword + Offset C										Radioext Segment										Checkword + Offset D									
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	AB	Text Address segment										Checkword + Offset B										PI Code										Checkword + Offset C										Radioext Segment										Checkword + Offset D									
3 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	Application Group Type										Checkword + Offset B										Message Bits										Checkword + Offset C										Application Identification (AID)										Checkword + Offset D										
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	ODA according to 3.1.4										Checkword + Offset B										PI Code										Checkword + Offset C										ODA according to 3.1.4										Checkword + Offset D										
4 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	Spare Bits										M/D code	Checkword + Offset B										M/D code, LSB is part of hour code										Checkword + Offset C										UTC and time offset										Checkword + Offset D									
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	ODA according to 3.1.4										Checkword + Offset B										PI Code										Checkword + Offset C										ODA according to 3.1.4										Checkword + Offset D										
5 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	Address										Checkword + Offset B										Transparent data segment										Checkword + Offset C										Transparent data segment										Checkword + Offset D										
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	Address										Checkword + Offset B										PI Code										Checkword + Offset C										Transparent data segment										Checkword + Offset D										
6 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	ODA according to 3.1.4										Checkword + Offset B										ODA according to 3.1.4										Checkword + Offset C										ODA according to 3.1.4										Checkword + Offset D										
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	ODA according to 3.1.4										Checkword + Offset B										PI Code										Checkword + Offset C										ODA according to 3.1.4										Checkword + Offset D										
7 A	PI Code		Checkword + Offset A										GTC	0	TP	PTY	Paging Segment address code										Checkword + Offset B										Paging										Checkword + Offset C										Paging										Checkword + Offset D										
B	PI Code		Checkword + Offset A										GTC	1	TP	PTY	ODA according to 3.1.4										Checkword + Offset B										PI Code										Checkword + Offset C										ODA according to 3.1.4										Checkword + Offset D										

3/7


FIGURE 2 B (ii)

8 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	Defined by CEN	Checkword + Offset B	Defined by CEN	Checkword + Offset C	Defined by CEN	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
9 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	EWS assigned by each country	Checkword + Offset B	EWS assigned by each country	Checkword + Offset C	EWS assigned by each country	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
10 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	Flag A/B	Checkword + Offset B	PTYN Segment	Checkword + Offset C	PTYN Segment	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	0 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
11 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
12 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
13 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	info field	Checkword + Offset B	Information Field	Checkword + Offset C	Information Field	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	ODA according to 3.1.4	Checkword + Offset B	PI Code	Checkword + Offset C	ODA according to 3.1.4	Checkword + Offset D
14 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	Variant Code	Checkword + Offset B	Information Block	Checkword + Offset C	Information Block	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	Unused	Checkword + Offset B	PI (TN)	Checkword + Offset C	PI (TN)	Checkword + Offset D
15 A	PI Code	Checkword + Offset A	GTC	0 TP	PTY	NOT Specified for compatibility with RBDS	Checkword + Offset B	PI (ON)	Checkword + Offset C	PI (ON)	Checkword + Offset D
B	PI Code	Checkword + Offset A	GTC	1 TP	PTY	MS	Checkword + Offset B	PI Code	Checkword + Offset C	Repeat Block 2	Checkword + Offset D

FIGURE 3


Group type	Group type code/version					Flagged in type 1A groups	Description
	A ₃	A ₂	A ₁	A ₀	B ₀		
0 A	0	0	0	0	0		Basic tuning and switching information only (see 3.1.5.1)
0 B	0	0	0	0	1		Basic tuning and switching information only (see 3.1.5.1)
1A	0	0	0	1	0		Programme Item Number and slow labelling codes only (see 3.1.5.2)
1B	0	0	0	1	1		Programme Item Number (see 3.1.5.2)
2 A	0	0	1	0	0		RadioText only (see 3.1.5.3)
2 B	0	0	1	0	1		RadioText only (see 3.1.5.3)
3 A	0	0	1	1	0		Applications Identification for ODA only (see 3.1.5.5)
3 B	0	0	1	1	1		Open Data Applications
4 A	0	1	0	0	0		Clock-time and date only (see 3.1.5.6)
4 B	0	1	0	0	1		Open Data Applications
5 A	0	1	0	1	0		Transparent Data Channels (32 channels) or ODA (see 3.1.5.8)
5 B	0	1	0	1	1		Transparent Data Channels (32 channels) or ODA (see 3.1.5.8)
6 A	0	1	1	0	0		In House applications or ODA (see 3.1.5.9)
6 B	0	1	1	0	1		In House applications or ODA (see 3.1.5.9)
7 A	0	1	1	1	0	Y	Radio Paging or ODA (see 3.1.5.10 and Annex M)
7 B	0	1	1	1	1		Open Data Applications
8 A	1	0	0	0	0	Y	Traffic Message Channel or ODA (see 3.1.5.12)
8 B	1	0	0	0	1		Open Data Applications
9 A	1	0	0	1	0	Y	Emergency Warning System or ODA (see 3.1.5.13)
9 B	1	0	0	1	1		Open Data Applications
10 A	1	0	1	0	0		Programme Type Name
10 B	1	0	1	0	1		Open Data Applications
11 A	1	0	1	1	0		Open Data Applications
11 B	1	0	1	1	1		Open Data Applications
12 A	1	1	0	0	0		Open Data Applications
12 B	1	1	0	0	1		Open Data Applications
13 A	1	1	0	1	0	Y	Enhanced Radio Paging or ODA (see Annex M)
13 B	1	1	0	1	1		Open Data Applications
14 A	1	1	1	0	0		Enhanced Other Networks information only (see 3.1.5.19)
14 B	1	1	1	0	1		Enhanced Other Networks information only (see 3.1.5.19)
15 A	1	1	1	1	0		Defined in RBDS only
15 B	1	1	1	1	1		Fast switching information only (see 3.1.5.20)

FIGURE 4




6/7

FIGURE 5



7/7

FIGURE 6



MAY 23 2007